SPP6307
P-Channel Enhancement Mode MOSFET

DESCRIPTION
The SPP6307 is the Dual P-Channel enhancement mode power field effect transistors are produced using high cell density , DMOS trench technology. This high density process is especially tailored to minimize on-state resistance and provide superior switching performance. These devices are particularly suited for low voltage applications such as notebook computer power management and other battery powered circuits where high-side switching , low in-line power loss, and resistance to transients are needed.

APPLICATIONS
- Drivers : Relays/Solenoids/Lamps/Hammers
- Power Supply Converter Circuits
- Load/Power Switching Cell Phones, Pagers

FEATURES
- P-Channel
  -20V/0.45A,$R_{DS(ON)}$= 0.65Ω@V_{GS}=-4.5V
  -20V/0.35A,$R_{DS(ON)}$= 0.90Ω@V_{GS}=-2.5V
  -20V/0.25A,$R_{DS(ON)}$= 1.5Ω@V_{GS}=-1.8V
- Super high density cell design for extremely low $R_{DS\ (ON)}$
- Exceptional on-resistance and maximum DC current capability
- ESD protected
- SOT-363 package design

PIN CONFIGURATION(SOT-363)





PART MARKING



Y : Year Code
W : Week Code

SPP6307
P-Channel Enhancement Mode MOSFET

PIN DESCRIPTION

Pin	Symbol	Description
1	S1	Source 1
2	G1	Gate 1
3	D2	Drain 2
4	S2	Source 2
5	G2	Gate 2
6	D1	Drain1

ORDERING INFORMATION

Part Number	Package	Part Marking
SPP6307S36RGB	SOT-363	07

※ SPP6307S36RGB : Tape Reel ; Pb – Free, Halogen – Fre

ABSOULTE MAXIMUM RATINGS

(T_A=25℃ Unless otherwise noted)

Parameter		Symbol	Typical	Unit
Drain-Source Voltage		V_{DSS}	-30	V
Gate –Source Voltage		V_{GSS}	±12	V
Continuous Drain Current(T_J=150℃)	T_A=25℃	I_D	-0.45	A
	T_A=80℃		-0.35	
Pulsed Drain Current		I_{DM}	-1.0	A
Continuous Source Current(Diode Conduction)		I_S	-0.3	A
Power Dissipation	T_A=25℃	P_D	0.27	W
	T_A=70℃		0.16	
Operating Junction Temperature		T_J	-55/150	℃
Storage Temperature Range		T_{STG}	-55/150	℃

ELECTRICAL CHARACTERISTICS

(T_A=25℃ Unless otherwise noted)

Parameter	Symbol	Conditions	Min.	Typ	Max.	Unit
Static						
Drain-Source Breakdown Voltage	$V_{(BR)DSS}$	V_{GS}=0V,I_D=-250uA	-30			V
Gate Threshold Voltage	$V_{GS(th)}$	V_{DS}=V_{GS},I_D=-250uA	-0.35		-1.0	
Gate Leakage Current	I_{GSS}	V_{DS}=0V,V_{GS}=±12V			±10	uA
Zero Gate Voltage Drain Current	I_{DSS}	V_{DS}=-24V,V_{GS}=0V			-1	uA
		V_{DS}=-24V,V_{GS}=0V T_J=55℃			-5	
On-State Drain Current	$I_{D(on)}$	V_{DS}≤ -4.5V,V_{GS} =-5V	-0.7			A
Drain-Source On-Resistance	$R_{DS(on)}$	V_{GS}=-4.5V,I_D=-0.45A			0.65	Ω
		V_{GS}=-2.5V,I_D=-0.35A			0.90	
		V_{GS}=-1.8V,I_D=-0.25A			1.50	
Forward Transconductance	gfs	V_{DS}=-10V,I_D=-0.25A		0.4		S
Diode Forward Voltage	V_{SD}	I_S=-0.15A,V_{GS}=0V		-0.8	-1.2	V
Dynamic						
Total Gate Charge	Q_g	V_{DS}=-10V,V_{GS}=-4.5V I_D=-0.6A		1.5	2.0	nC
Gate-Source Charge	Q_{gs}			0.3		
Gate-Drain Charge	Q_{gd}			0.35		
Turn-On Time	$t_{d(on)}$	V_{DD}=-10V, R_L=10Ω , I_D=-0.4A V_{GEN}=-4.5V, R_G=6Ω		5	10	nS
	t_r			15	25	
Turn-Off Time	$t_{d(off)}$			8	15	
	t_f			1.4	1.8	

TYPICAL CHARACTERISTICS









TYPICAL CHARACTERISTICS









TYPICAL CHARACTERISTICS







SYNC Power Corporation
7F-2, No.3-1, Park Street
NanKang District (NKSP), Taipei, Taiwan 115
Phone: 886-2-2655-8178
Fax: 886-2-2655-8468
© http://www.syncpower.com